

TRP 8252S/55S/57S
 OPTIONAL FILTER CONFIGURATIONS

	BANDWIDTH (Hz)					X-TAL FILTERS					RX/EX STATUS					SM601D			
	AM/WIDE	INTER-MEDIATE	NARROW	VERY NARROW	TELEX	X1 AM/WIDE	X2 INTER.	X3 NARROW	X4 TELEX + (V. NAR/NAR)	X5 SSB +(INTER)	CK X5	CK X4	CK X3	CK X2	JUMPER **)				
														J1	J2	J3	J4	J9	
1 (STD)	+/-2.7k	+/-1.2k	+/-250	+/-150	+/-150	383 571 0X		383 582 3X df=-1.5k	385 247 6X df=-1.5k	385 112 0X	0	0	0	1	1	1	0	1	1
2	+/-2.7k	+/-1.2k	+/-250	+/-250	+/-250	383 571 0X			383 582 3X df=-1.5k	385 112 0X	0	0	1	1	0	1	1	1	1
3	+/-2.7k	+/-1.2k	+/-250	- *)	+/-400	383 571 0X		383 582 3X df=-1.5k	385 201 7X df=-1.5k	385 112 0X	0	0	0	1	1	1	0	1	1
4	+/-2.7k	+/-1.2k	+/-500	+/-150	+/-150	383 571 0X		385 201 0X df=0	385 247 6X df=-1.5k	385 112 0X	0	0	0	1	1	1	1	1	1
5	+/-4k	+/-1.2k	+/-500	+/-150	+/-150	383 582 4X		385 201 0X df=0	385 247 6X df=-1.5k	385 112 0X	0	0	0	1	1	1	1	1	0
6	+/-4k	+/-2.7k	+/-500	+/-150	+/-150	383 582 4X	385 111 9X df=0	385 201 0X df=0	385 247 6X df=-1.5k	385 112 0X	0	0	0	0	1	1	1	1	0
7	+/-2.7k	+/-1.2k	+/-500	+/-250	+/-250	383 571 0X		385 201 0X df=0	383 582 3X df=-1.5k	385 112 0X	0	0	0	1	1	1	1	1	1

*) VERY NARROW KEY MUST BE DISABLED IN CONFIGURATION PROM.
 **) Re JUMPERS : A "0" DENOTES THAT THE JUMPER MUST BE MADE.

FORDELT TIL: OH, BF, CO, JH, JS, EO, POJ, FB, KK, JC, BS, JON, BB